

HAI TECHNICAL UPDATES

"Omni Version 1.6 Firmware Release"

ADD THIS DOCUMENT TO YOUR OMNI OWNER'S MANUAL DESCRIPTION

The Version 1.6 firmware adds the following new feature to Omni automation controllers:

- Supports direct lighting level control using the X-10 preset dim command

LIGHTING LEVEL

To enter the control menu, from the top-level display or from the main menu, press the 1 (CONTROL) key on the console keypad. Omni will automatically display the first named item in that list. The down arrow key can then be used to scroll through the list and the ' #' key is used to select the item. If the specific item number is known, enter the item number followed by the ' #' key, or scroll up and down among the named items.

After the unit has been selected, press the ' #' key. The console will display:

Porch Light (Unit Name)

0=OFF 1=ON 2=DIM 3=BRT

Porch Light (Unit Name)

4=LVL 9=TIM #=STA

Press the 4 key to set the desired lighting level of the specified unit.

Enter a number (0-100) to indicate the lighting level (intensity) of the unit.

LIGHTING LEVEL:

0-100%

0 = No Light

50 = Light to half intensity

100 = Light to full intensity

The console will beep and the lighting level will be adjusted.

The top line of the console display will read:

Porch Light LVL 65