

HAI TECHNICAL UPDATES

"Omni Version 1.4e Firmware Release"

ADD THIS DOCUMENT TO YOUR OMNI OWNER'S MANUAL

NEW FEATURES

The Omni Version 1.4e software adds the following new features to the Omni:

- Ability to create yearly programs
- Ability to execute programs before/after sunrise and sunset

YEARLY PROGRAMS

When creating a timed automation program, you may specify that the program run only once or every year on that date.

TIME: 8:00 AM

HHMM Up=RISE/AM Dn=SET/PM

Select 2 (DATE/DAY) to enter a new date or days of week.

DATE: 10/15

MMDD Dn=DAY

Next, specify if the program will run once (on the specified date and then be deleted) or if the program will run every year on the specified date (yearly).

RUN PROGRAM

1=ONCE 2=YEARLY

BEFORE/AFTER SUNRISE AND SUNSET

When creating a timed automation program and if the desired time is the time in which sunrise or sunset will occur, press the up arrow key for sunrise, or the down arrow key for sunset before entering a time.

TIME: 12:00 AM

HHMM Up=RISE/AM Dn=SET/PM

You may also choose to have the program execute up to 120 minutes before or after the time of sunrise or sunset.

SUNSET

1=BEFORE 2=AFTER #=AT

If the 1(BEFORE) or 2(AFTER) key is selected, you will be prompted to select the amount of minutes:

ENTER OFFSET:

0-120 MINUTES

When entering a time of day, AM/PM must be specified for the time if the AM/PM format is being used. Otherwise the entered time should be 13:00-23:59.